

Product data sheet

Characteristics

15609

hour counter - mechanical 7 digit display - 12..36 VDC



Main

Range	PowerLogic
Device short name	CH
Product or component type	Hour counter
Range compatibility	Prisma (Prisma P) door Prisma (Prisma G) door
Type of measurement	Operating time
Display type	Electromechanical 7 digit(s), number of decimal = 2

Complementary

Reset	Without
[Us] rated supply voltage	12...36 V DC
Power consumption in VA	0.02 VA at 12 V 0.3 VA at 36 V
Mounting support	Front face

Environment

IP degree of protection	Front face: IP65
Width	48 mm
Height	48 mm
Depth	39 mm

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	5.6 cm
Package 1 Width	6.2 cm
Package 1 Length	6.4 cm
Package 1 Weight	60.0 g
Unit Type of Package 2	S03
Number of Units in Package 2	96
Package 2 Height	30.0 cm
Package 2 Width	30.0 cm
Package 2 Length	40.0 cm
Package 2 Weight	6.2 kg

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Offer Sustainability

REACH Regulation	REACH Declaration
REACH free of SVHC	Yes
EU RoHS Directive	Compliant EU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes
China RoHS Regulation	China RoHS Declaration
RoHS exemption information	Yes
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Contractual warranty

Warranty	18 months
----------	-----------