

### Product data sheet Characteristics

## PDL29LBK

# Batten Lampholder, Lighting, 230/240VAC, Bayonet Base



#### Main

| Widin                     |                              |
|---------------------------|------------------------------|
| Range of product          | PDL Lighting and Accessories |
| Product or component type | Button module                |
| Colour tint               | Black                        |
| Load type                 | 150 W lamp                   |
| Quantity per set          | Set of 20                    |
| Type of packing           | Carton                       |

Complementary

| Material                       | Thermoplastic           |  |  |
|--------------------------------|-------------------------|--|--|
| Surface finish                 | Glossy                  |  |  |
| [Ue] rated operational voltage | 230/240 V AC 50 Hz      |  |  |
| Network number of phases       | 1 phase                 |  |  |
| Fixing mode                    | By screws               |  |  |
| Device mounting                | Surface                 |  |  |
| Diameter                       | 66 mm                   |  |  |
| Fixing center                  | 50 mm                   |  |  |
| Connections - terminals        | 4 x 1 mm screw terminal |  |  |

#### **Packing Units**

| Unit Type of Package 1       | PCE      |  |
|------------------------------|----------|--|
| Number of Units in Package 1 | 1        |  |
| Package 1 Height             | 7.0 cm   |  |
| Package 1 Width              | 7.0 cm   |  |
| Package 1 Length             | 7.0 cm   |  |
| Package 1 Weight             | 0.052 kg |  |

#### Offer Sustainability

| Offer Sustainability |                     |  |
|----------------------|---------------------|--|
| EU RoHS Directive    | Under investigation |  |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not inherenced as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the documentation is not be used to perform the appropriate and complete risk analysis, evaluation of the products with respect to the relevant specific application or use thereof. Neither Schmeider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.