



Main

| | |
|---------------------------------------|---|
| Range compatibility | Harmony XVB Harmony XVD Harmony XVP |
| Accessory / separate part designation | Protected LED bulb |
| Accessory / separate part type | LED bulb |
| Accessory / separate part category | Lighting accessories |
| Accessory / separate part destination | Beacon and indicator bank |
| [Us] rated supply voltage | 24 V AC/DC |
| Signalling type | Flashing |
| Signalling colour | White |
| Sale per indivisible quantity | 1 |

Complementary

| | |
|----------------|----------|
| Bulb base | BA 15d |
| Product weight | 0.015 kg |

Environment

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.